

PRODUCT-DETAILS

AMTD-1

AMTD-1 Digital Ammeter



Γενικές Πληροφορίες

Extended Product Type	AMTD-1
Product ID	2CSM320000R1011
EAN	8012542620501
Catalog Description	AMTD-1 Digital Ammeter
Long Description	AMTD-1 is a digital ammeter for ac networks

Technical

Product Name	Digital Ammeter
Current Type	AC
Frequency (f)	35 ... 400 Hz
Power Loss	4 W
Accuracy	±0,5% F.S. ±1digit at 25 °C
Measurement Scale	End 600 A
Measuring Range	5...600 A
Meter Type	Digital
Mounting Type	DIN-Rail
Model Number	DIN rail

Environmental

Ambient Air Temperature	Operation -40 ... 55 °C
Degree of Protection	IP20
RoHS Status	Following EU Directive 2002/95/EC August 18, 2005 and amendment
Environmental Information	See RoHS Information

Dimensions

Width in Number of Modular Spacings	3
Product Net Width	52.5 mm
Product Net Height	26.5 mm
Product Net Depth / Length	61.5 mm
Product Net Weight	0.100 kg

Container Information

Package Level 1 Units	box 1 piece
Package Level 1 Width	0.058 m
Package Level 1 Height	0.085 m
Package Level 1 Depth / Length	0.053 m
Package Level 1 Gross Weight	0.3 kg
Package Level 1 EAN	8012542620501

Ordering

Minimum Order Quantity	1 piece
Customs Tariff Number	90303100
E-Number (Finland)	6701005
Country of Origin	Romania (RO)
Selling Unit of Measure	piece

Certificates and Declarations (Document Number)

Declaration of Conformity - CE	9AKK106713A5697
Environmental Information	See RoHS Information
Instructions and Manuals	2CSG445001D5601
RoHS Information	2CSC445007K0201

Popular Downloads

Data Sheet, Technical Information	9AKK107046A0430
Instructions and Manuals	2CSG445001D5601

Classifications

ETIM 6	EC002292 - Ampere meter for installation
ETIM 7	EC002292 - Ampere meter for installation
ETIM 8	EC002292 - Ampere meter for installation

WEEE Category	5. Small Equipment (No External Dimension More Than 50 cm)
WEEE B2C / B2B	Business To Consumer
CN8	90303100
Object Classification Code	P

Κατηγορίες

Προϊόντα και Συστήματα Χαμηλής Τάσης → Ραγούλικά → Μετρητές Ενέργειας για Ράγα DIN → DIN-Rail single function instruments

