

PRODUCT DATASHEET

SMART+ WiFi Remote Controller DIM

SMART+ WiFi Remote Controller | Remote Controller with WiFi technology for dimming



Areas of application

- Smart Home in indoor and outdoor
- Controls up to 15 compatible SMART+ WiFi products by contactless pairing

Product benefits

- Wireless control of compatible SMART+ WiFi products
- Control of SMART+ Wifi products without using voice control and APP

Product features

- On/off and dimming
- Battery-powered (2x AAA batteries)
- Controllable up to 15 SMART+ WiFi products
- Network protocol: WiFi




TECHNICAL DATA

Electrical data

Nominal voltage	3 V
Mains frequency	0 Hz

Dimensions & Weight



Product weight	31.00 g
Length	14.00 mm
Width	37.00 mm
Height	130.00 mm

Lifespan

Number of switching cycles	100000
----------------------------	--------

Colors & materials

Product color	White
Cover material	Polycarbonate (PC)

Temperatures & operating conditions

Ambient temperature range	-10...+35 °C
---------------------------	--------------

Capabilities

Dimmable	No
----------	----



Certificates & Standards

Standards	CE
Type of protection	IP20

EQUIPMENT / ACCESSORIES

- LEDVANCE SMART+ WiFi APP required (only for the configuration of SMART+ WiFi products)
 - Batteries are not included
-

DOWNLOAD DATA

DOWNLOAD DATA	
	User instruction
	Declarations of conformity

LOGISTICAL DATA

Product code	Packaging unit (Pieces/Unit)	Dimensions (length x width x height)	Gross weight	Volume
4058075526938	Folding box 1	78 mm x 143 mm x 61 mm	90.00 g	0.68 dm ³
4058075526945	Shipping box 4	166 mm x 153 mm x 138 mm	446.00 g	3.50 dm ³
4058075526952	Shipping box 32	344 mm x 318 mm x 292 mm	3931.00 g	31.94 dm ³

The mentioned product code describes the smallest quantity unit which can be ordered. One shipping unit can contain one or more single products. When placing an order, for the quantity please enter single or multiples of a shipping unit.

DISCLAIMER

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.